(Français Au Verso)

NOTES:

1. When handset is removed contact gf breaks last.
2. Use MIW Cord for strapping.
3. The SL and SL-R Ringer Leads are factory wired to terminals S and S. These terminals are spare. If use of these terminals are required for other wiring changes remove ringer leads tape and store ensuring the stored leads are dressed to avoid interference with other components.
4. Ground may be omitted if not required for service; not required for protection on Dial Light Transformer.
5. The 1702BQ1A and 2702BQA tel. sets are identical except that the 1702BQ1A tel. set is equipped with a 25H4 dial (10 button) and the 2702BQA tel. set is equipped with a 35H4 dial (12 button and a one piece housing).
6. To modify telephone set as shown in Fig. 4, rewire the set according to Table C.

TABLE C

Table of Wiring Changes For 1A1 or 1A2 & 3A Speakerphone

Lead	From	To	REF.
SL-R	S	—	Note 3
SL-BK	C	S	
BK	G	L¹	
SL-Y	A	G	
Strap	L²	3	Note 2
Strap	G	C	Note 2




Fig. 4 — 1702BQ1A Tel. Set And 2702BQA Tel. Set Equipped With QNB17A Network Connections For 1A1 or 1A2 KTS And 3A Speakerphone